ANNUNCIATION AND NOTIFICATION FEATURES

ANNUNCIATORS, ALARM PANELS, INDICATORS, AND I/O MODULES	SEL-2522	SEL-2523	SEL-2533	SEL-2506‡	SEL-2516‡	SEL-2595‡
APPLICATIONS						
Local Visual Indication	•	•	•	•	•	•
Remote Visual Indication		•	•	•	•	•
Local Audible Indication	•	•	•			
Remote Audible Indication	•	•	•			
Telephone Dial-Out Messages		•	•			
Local SELogic® Control Equations and Time Tagging		•	•			
MOUNTING AND LABELING						
Rack Mount	+	+		+	+	+
Panel Mount	+	+	•			
Projection Panel Mount				+	+	+
User-Defined Slide-In Labels	•	•	•	•	•	•
INPUTS, OUTPUTS, AND HMI						
General-Purpose Digital Inputs	36	42	14+	8	8	8
Acknowledge, Reset, Test Digital Inputs	3	6	4+			
General-Purpose Digital Outputs	1	11	14+	8	8	8
Alarm Digital Output	1	1	1	1	1	1
General Display LEDs/Windows	36	36	10	8	8	8
Enabled LED	1	1	1	1	1	1
Other Communication/Status LEDs				5	4	5
Pushbuttons	3	4	4			
Base Serial Ports		3	3	1	1	1
Optional Additional EIA-232 or EIA-485 Port		1	1			
IRIG-B Time Input		1	1			
ISA Annunciation Alarm Sequence Choices	2	6	All			
SERIAL COMMUNICATIONS PROTOCOLS						
SEL Mirrored Bits® Communications		•	•	•		
SEL Fast Messages		•	•		•	
Send SEL Messenger Points		•	•			
Modbus® RTU		•	•			
DNP3 Level 2 Outstation		+	+			

• Standard Feature + Model Option

‡See I/O Processor and Controller section for more information